

¡Ármelo usted mismo!

¡Do it yourself!



Entrepuestos:
Trace las alturas, nivele y marque cada 30 cm aprox iniciando a 3 cm de la esquina.

Shelves:
Mark out height, level shelves and mark holes where the "wall clips" will be installed (the holes must be at least 12" apart).

1



Perfore la pared con broca para muro de 1/4". Introduzca un "chazo J" y colóquelo un "clavo roscado".

Drill each hole in the wall with a 1/4" drill bit. Insert a "wall clip" and then the "screw pin".



Muro de Yeso - Drywall and Plaster

Atornille el clavo roscado en el "chazo J".
Screw supplied "screw pin" into the "wall clip".



Muro Sólido - Masonry Wall

Martille el clavo roscado en el "chazo J".
Hammer the "screw pin" into the "wall clip".



Si es necesario corte los entrepaños y coloque "topes" plásticos.

If necessary cut the shelf, cover the ends with the corresponding "ends caps".

instale los entrepaños, haciendo presión sobre los "chazos J".

Set the back of the shelving into the "wall clips" and press down until it locks in place.

3



Ubique el "soporte lateral" en el entrepaño, nivele y marque los dos orificios del soporte, perfore con broca 1/4" y fije con chazos y tornillos.

Place a "wall bracket" on the shelf's front and level it, mark hole locations, drilling with drill bit 1/4", insert a wall clip into each hole and screw bracket into the place.

4



Haga sánduche con los "escudos", fije el "soporte diagonal" al entrepaño, con tornillo y tuerca, luego nivele y fije a la pared con chazo y tornillo.

Snap in place the shelf front between "joiner plates" attach "support bracket" with screw and nut. Level and lower end to "wall clip" and "screw".

5



Haga sánduche con los "escudos", nivele y perfore el paral con broca para metal de 1/8" y fije con tornillo.

Snap in place the shelf front between "joiner plates" attach. Use the "joiner plates" hole as a guide and insert the screw. Once the shelf is leveled, drilling a 1/8" hole into the pole.

6

Se instala en obra blanca y no necesita mantenimiento posterior.
This configuration is installed on ready finish surface and no required future maintenance.